

user guide



**hp** embedded  
web server for  
**hp** LaserJet  
printers



---

hp embedded web server  
for hp LaserJet printers

---

user guide

**Trademark Credits**

Microsoft ® is a U.S. registered trademark of Microsoft Corporation.

Netscape is a U.S. trademark of Netscape Communications Corporation.

UNIX ® is a registered trademark of the Open Group.

Windows ® and Windows NT ® are U.S. registered trademarks of Microsoft Corp.

**Warranty**

The information contained in this document or software is subject to change without notice.

Hewlett-Packard makes no warranty of any kind with respect to this information.

HEWLETT-PACKARD SPECIFICALLY DISCLAIMS THE IMPLIED WARRANTY OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

Hewlett-Packard shall not be liable for any direct, indirect, incidental, consequential, or other damage alleged in connection with the furnishing or use of this information.

**©Copyright Hewlett-Packard Company, 2001**

All Rights Reserved.

Reproduction, adaptation, or translation without prior written permission is prohibited, except as allowed under the copyright laws.

First Edition, January 2001

# Contents

Introducing the HP Embedded Web Server .....	3
Overview.....	3
Features .....	4
Additional Features with a Permanent Storage Device .....	5
Introducing ChaiVM (Embedded Virtual Machine).....	6
Accessing the HP Embedded Web Server .....	7
System Requirements .....	7
Viewing the HP Embedded Web Server.....	7
Navigating the HP Embedded Web Server.....	8
Viewing Printer Status with the Home Pages.....	9
Overview.....	9
Printer Status.....	10
Configuration Page .....	11
Supplies Status.....	12
Event Log .....	13
Usage Page.....	14
Device Information.....	15
Configuring the Printer with the Device Pages.....	17
Overview.....	17
Configure Printer.....	18
Selecting Paper Size .....	20
Alerts .....	21
Configuring Alert Notification .....	23
Refining Event Notification .....	27
Email.....	30
Configuring Outgoing Mail .....	31
Configuring Incoming Mail .....	32
Using Email Command and Response.....	33
Security.....	35
Other Links .....	36
Adding a Link.....	37
Removing a Link.....	37
Device Information.....	38
Language.....	39
Managing the Network with the Networking Pages.....	41
Overview.....	41

Appendix A – HP Web JetAdmin and the HP Embedded Web Server.....	43
Appendix B – How Do I? .....	45
Sharing Printer Information.....	45
Setting Up the Printer to Send E-mail Messages.....	46
Setting Up the Printer to Receive and Respond to E-mail Messages.	52
Index .....	57

# Introducing the HP Embedded Web Server

## Overview


A *web server* provides an environment in which web programs may run, much in the same way that an operating system, such as Windows, provides an environment for programs to run on your PC. The output from these programs can then be displayed by a web browser, such as Microsoft Internet Explorer or Netscape Navigator.

When a web server is “embedded”, that means it resides on a hardware device (such as a printer) or in firmware, rather than as software that is loaded on a network server.

The advantage of an *embedded web server* is that it provides an interface to the printer that anyone with a network-connected PC and a standard web browser can access. There is no special software to install or configure.

The HP Embedded Web Server helps you to display status information, change settings, and manage the printer from the comfort of your PC.

The top of the Home page is shown below.



---

### Note

The HP Embedded Web Server screens shown in this guide are for the HP Color LaserJet 4550 series printer. If you are using a different printer model, you will notice slight variations in the embedded web server appearance and features.

---

## Features

The HP Embedded Web Server allows you to view printer and network card status and manage printing functions from your PC. With the HP Embedded Web Server, you can do the following:

- View printer control panel messages and status lights.
- Determine the remaining life on all consumables.
- Order consumables.
- View and change tray configurations.
- View and change the printer configuration.
- View and print internal pages.
- Receive notification of printer events.
- Add or customize links to other web sites.
- Select the language in which to display the embedded web server pages.
- View and change network card configuration.

## Additional Features with a Permanent Storage Device

If you have a permanent storage device installed in your printer (such as a hard disk), you can view, set up, and retain additional information.

- **Usage Page**—With a hard disk, you can view the Usage Page, which gives a page count for each size of media that has passed through the printer and shows the average percentage of toner coverage per page for each color; without the extra storage, the Usage Page is not available.
- **Alerts**—With a hard disk, you can set up four different notification lists, with up to 20 recipients on each of the four lists; without the extra storage, you can send alerts to only two e-mail addresses.
- **Other Links**—With a hard disk, you can add up to five additional links to the web sites of your choice; without the extra storage, you can add one additional link.

A hard disk may have shipped with your printer, depending on your printer model. To find out if you have a hard disk, print a configuration page. (Or view the embedded web server Configuration Page. See page 11.) The configuration page provides a summary of all installed accessories.

### To print a configuration page:

1. On the printer control panel, press **Menu** until INFORMATION MENU displays.
2. Press **Item** until PRINT CONFIGURATION displays.
3. Press **Select** to print the configuration page. After the process is completed, the printer will return to the READY state.

If your printer does not have a hard disk, you can order one. For more information, see the user guide that came with your printer, or go to: [http://www.hp.com/go/buy\\_hp](http://www.hp.com/go/buy_hp) (inside the United States) or <http://www.hp.com/country/us/eng/othercountriesbuy.htm>.

## Introducing ChaiVM (Embedded Virtual Machine)

The printer also includes an embedded virtual machine for running Java™ applications, called ChaiVM. This infrastructure inside the printer allows for development of extended solutions, helps solve problems, and makes printer management easier. The embedded virtual machine has been specifically designed to make communication over the network or Internet easy.

Once you have this generic virtual machine operating system, you have several new capabilities:

- Applications can be developed on a PC with confidence that they will run on the embedded virtual machine. No custom development environment is required. A Java application that can run on ChaiVM virtual machine in a Windows 98 environment can also run in a Macintosh or a printer. This makes it easier and faster for developers to create custom printer capabilities.
- Printer firmware, or other applications, can be released and updated later.
- All of this can be done dynamically: an application can be sent to run on the embedded virtual machine (a self-test diagnostic program, for example), and the application can be deleted when it is done. Applications don't have to be permanently stored on the printer.

These capabilities apply to all printers with ChaiVM.

# Accessing the HP Embedded Web Server

## System Requirements

To use the HP Embedded Web Server, you must have the following:

- a TCP/IP-based network
- a web browser installed on your computer, preferably either Netscape Navigator 4.7X or Microsoft Internet Explorer 5.0X and above

---

### Note

The embedded web server can be accessed from any operating system that supports the TCP/IP protocol and a web browser.


The embedded web server does not support IPX-based network printer connections and cannot be accessed with a parallel cable.

You cannot view the embedded web server pages from outside a firewall.

---

## Viewing the HP Embedded Web Server

1. Launch your web browser.
2. In the **Address:** or **Go to:** field, type the IP address assigned to the printer (for example: `http://192.168.1.1`) or the host name (for example: `http://myprinter`).



If you do not know the IP address for the printer, it is listed on the printer configuration page under Protocol Information in the TCP/IP section.

### To print a configuration page:

- a. On the printer control panel, press **Menu** until INFORMATION MENU displays.
- b. Press **Item** until PRINT CONFIGURATION displays.
- c. Press **Select** to print the configuration page. After the process is completed, the printer will return to the READY state.

# Navigating the HP Embedded Web Server

The HP Embedded Web Server has three sets of internal web pages for viewing printer information and for changing configuration options. You can access these pages by clicking one of the following three tabs: Home, Device, and Networking.



- The **Home** pages are the informational pages for the printer. You cannot configure the printer from these pages. (For more information, see page 9.)
- The **Device** pages allow you to configure the printer from your PC. (For more information, see page 17.)
- The **Networking** pages allow you to view network status and configure the printer's network card from your PC. (For more information, see page 41.)

These pages may also provide additional links. For more information, see "Other Links" on page 36.

---

## Note

The HP Embedded Web Server screens shown in this guide are for the HP Color LaserJet 4550 series printer. If you are using a different printer model, you will notice slight variations in the embedded web server appearance and features.

---

# Viewing Printer Status with the Home Pages

## Overview

The Home pages are the informational pages for the printer. You cannot configure the printer from these pages. The table below lists each of the Home pages and describes its features. For more information, see the page indicated.

Home Page	Features
Printer Status (page 10)	Provides remote Go and Job Cancel functions; displays control panel messages and status lights (including help); allows you to set the refresh rate; and displays consumable life levels, input tray configurations, and installed accessories.
Configuration Page (page 11)	Displays all printer configuration settings.
Supplies Status (page 12)	Shows consumables levels and assists with consumables ordering.
Event Log (page 13)	Shows the most recent printer events and errors.
Usage Page (page 14)	Displays the printer's name and serial number, gives a page count for each size of media that has passed through the printer, and shows the average percentage of toner coverage per page for each color. (This page is only available if your printer has a permanent storage device installed.)
Device Information (page 15)	Displays the device description, asset number, company name, contact person, and the printer's IP address, model, number, and serial number.

# Printer Status

Under **Control Panel**, the messages and status lights that currently appear on the printer control panel are displayed. Click **Control Panel Help** to view any help that is currently available on the printer control panel. (This appears at the bottom of the screen.)

The screenshot shows the HP Color LaserJet 4550 web interface. At the top, it displays the HP logo, the printer model 'HP Color LaserJet 4550', and the IP address '192.168.1.1'. Below this are navigation tabs for 'Home', 'Device', and 'Networking'. A left-hand menu contains links for 'Printer Status', 'Configuration Page', 'Supplies Status', 'Event Log', 'Usage Page', and 'Device Information'. The main content area is divided into sections: 'Control Panel' (showing 'READY' status and 'Go', 'Data', 'Attention' buttons), 'Supplies' (a table of consumables with progress bars), 'Media' (a table of input/output bins), and 'Capabilities' (a list of installed accessories). A 'Control Panel Help' section is at the bottom.

**Control Panel**

READY

Ready Data Attention

Go

Control Panel Help

Refresh Control Panel

Help

Set Refresh Rate: 0 minutes

Apply Cancel

**Supplies**

	% of Life Remaining
Black	78%
Cyan	55%
Magenta	48%
Yellow	56%
Drum Kit	46%
Fuser Kit	99%
Transfer Kit	99%

**Media**

Status	Input/Output	Size	Type
OK	TRAY 3	LETTER	PLAIN
OK	TRAY 2	A4	PLAIN
OK	TRAY 1	LETTER	PLAIN
OK	STANDARD OUTBIN	N/A	N/A

**Capabilities**

- DISK Storage: 3102 MB Capacity
- DIMM Slot 1: Side 1: Empty
- DIMM Slot 1: Side 2: Empty
- DIMM Slot 2: Side 1: 128 MB SDRAM
- DIMM Slot 2: Side 2: Empty

**Control Panel Help**

THIS PRINTER FEATURES AN ONLINE HELP SYSTEM. MESSAGES MARKED WITH ? HAVE ONLINE HELP AVAILABLE. WHENEVER ? APPEARS, PRESS ? (ITEM KEY) TO VIEW HELP MESSAGES. EXIT HELP BY PRESSING GO.

**Annotations:**


- You can click the printer's Go button to continue printing or to begin a print job. The Job Cancel button must be enabled from the Security page. (From the top of the screen, click Device, then on the left navigational bar, click Security.)
- You can set the rate at which the embedded web server will check the printer status. (Enter the number of minutes and click Apply.)
- Displays the percentage of life remaining for each consumable.
- Displays the status and configuration information for the input trays and output bins.
- Shows which accessories are installed in the printer.
- Displays any help that is currently available on the printer control panel when you press ? (Item key).

# Configuration Page

Use the Configuration Page to view current printer settings, to help troubleshoot printer problems, or to verify installation of optional accessories, such as memory (DIMMs) or paper handling devices.

## Note

You can send the Configuration Page to anyone you like via e-mail. See page 45 for more information.



**HP invent**

HP Color LaserJet 4550 / 192.168.1.1  
**HP Color LaserJet 4550**

**Home** Device Networking

**Printer Status**  
Configuration Page  
Supplies Status  
Event Log  
Usage Page  
Device Information

**Other Links**  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

**Configuration Page**

**Printer Information**  
Firmware Datecode: 20001019 01.003.0  
Jam Recovery: OFF  
Print PS Errors: OFF  
Page Count: 4953  
Color Page Count: 36  
Product Name: HP Color LaserJet 4550  
Printer Name: HP Color LaserJet 4550  
Printer Number: CXXXXA  
Resolution: 600  
Printer Serial Number: XXXXXXXXXXXX  
HP JetSend Address: 192.168.1.1

**Installed Personalities and Options**  
PCL (20000828)  
PCLXL (20000828)  
PS (20000828)  
DIMM Slot 2: Side 1 : 128 MB SDRAM  
DIMM Slot 2: Side 2: Empty  
DIMM Slot 3: Side 1 : 16 MB ROM  
DIMM Slot 3: Side 2 : 0 MB SDRAM  
EIO 1: HP C2985B  
EIO 2: HP JetDirect J4169A  
DISK Storage: 3102 MB Capacity

**Security**  
Control Panel Lock: DISABLED  
Control Panel Password: DISABLED  
Device Type: DISK Write Protect: DISABLED

**Memory**  
Total Memory: 128 MB  
DWS: 82.10

**Paper Trays and Options**  
Mopier: ON  
Default Paper Size: LETTER  
Tray 1 (LETTER)  
Tray 2 (A4)  
Tray 3 (LETTER)  
Input Trays:  
1: TRAY 1, 150 Sheets  
2: TRAY 2, 250 Sheets  
3: TRAY 3, 500 Sheets  
Output Bins:  
1: STANDARD, 250 Sheets, Face Down

**Density Settings**  
Black: 0  
Cyan: 0  
Magenta: 0  
Yellow: 0

# Supplies Status

The Supplies Status page shows the levels remaining for all consumables and the HP Part Numbers for each consumable. (It is helpful to have the part numbers available when it is time to order supplies.)

HP Color LaserJet 4550 / 192.168.1.1  
**HP Color LaserJet 4550**

Home Device Networking

**Supplies Status Page**  
 Hewlett-Packard Supplies can be ordered on the internet at <https://www.hp.com/go/ordersupplies-na> or by calling Hewlett-Packard. (Please refer to your printer User Manual for the telephone number).

*For highest print quality always use genuine Hewlett-Packard LaserJet supplies.*

**Cartridge Information**

	% of Life Remaining	HP Part Numbers:
Black	 78%	Black Toner Cartridge HP C4191A
Cyan	 55%	Cyan Toner Cartridge HP C4192A
Magenta	 48%	Magenta Toner Cartridge HP C4193A
Yellow	 56%	Yellow Toner Cartridge HP C4194A

**Other Supplies Information**

Drum Kit	 46%	Drum Kit HP C4195A
Transfer Kit	 99%	Transfer Kit HP C4196A
Fuser Kit	 99%	Fuser Kit HP 120V C4197A 220V C4198A

**Printer Information**

Total Printer Page Count:	4953
Pages printed in Color:	36
Pages printed in B&W:	4917
Printer Serial Number:	XXXXXXXXXX

Please return your used HP cartridge to Hewlett-Packard. For more information see: [http://www.hp.com/ljsupplies/planet\\_recycle.html](http://www.hp.com/ljsupplies/planet_recycle.html)

**Other Links**  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

**To order supplies over the Internet, click the Order Supplies link.**

# Event Log

The Event Log displays the most recent printer events, including printer jams, service errors, and other printer errors.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Printer Status  
Configuration Page  
Supplies Status  
Event Log  
Usage Page  
Device Information

**Event Log Page**  
Number of Entries in Use: 0  
Maximum Number of Entries: 50  
EVENT LOG EMPTY

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

For quick access to more information regarding error messages, click the [Solve A Problem](#) link, then select Error Messages. (This link takes you to hp.com on the World Wide Web; it is not part of the embedded web server.)

# Usage Page

The Usage Page displays the printer's name and serial number, gives a page count for each size of media that has passed through the printer, and shows the average percentage of toner coverage per page for each color.

**Note**

The Usage Page is only available if your printer has a permanent storage device (such as a hard disk) installed.

HP Color LaserJet 4550 / 192.168.1.1  
**HP Color LaserJet 4550**

Home Device Networking

**Usage Page**

**Identification**  
 S/N: XXXXXXXXXXXX  
 Product Name: HP Color LaserJet 4550  
 Printer Name: HP Color LaserJet 4550

**Usage Totals**

PRINTER Page Size	Count	SIMPLEX		DUPLEX		Total
		Units	Count	Units	Count	
UNKNWN	0	1.0	0	2.0	0.0	0.0
LETTER	12	1.0	11	2.0	34.0	0.0
LEGAL	0	1.3	0	2.6	0.0	0.0
A4	0	1.0	5	2.0	10.0	0.0
EXEC	0	0.8	0	1.6	0.0	0.0
COM10	0	0.4	0	0.8	0.0	0.0
MONARC	0	0.3	0	0.6	0.0	0.0
C5	0	0.6	0	1.2	0.0	0.0
DL	0	0.4	0	0.8	0.0	0.0
JISB5	0	0.7	0	1.4	0.0	0.0
B5	0	0.7	0	1.4	0.0	0.0
CUSTOM	0	1.0	0	2.0	0.0	0.0
A5	0	0.5	0	1.0	0.0	0.0
16K	0	0.8	0	1.6	0.0	0.0
JEXEC	0	1.1	0	2.2	0.0	0.0
<b>TOTAL PRINTER USAGE</b>						<b>44.0</b>

**Toner Coverage:**  
 Black Coverage 7.639  
 Cyan Coverage 9.123  
 Magenta Coverage 9.285  
 Yellow Coverage 9.487

Usage totals are displayed for each media size. (Shows the number of pages that were printed on one side, the number that were printed on two sides (duplexed), and totals of the two printing methods.)

Displays the average percentage of toner coverage per page for each color.

(This value is not separated for color and monochrome pages but is combined into one value for all pages printed.)

# Device Information

The Device Information page displays the device description, asset number, company name, contact person, and the printer's IP address, model, number, and serial number.

## Note

The device description, asset number, company name, and contact person must be entered from the Device pages. (From the top of the screen, click **Device**, then on the left navigational bar, click **Device Information**. See page 38 for more information.)

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Printer Status  
Configuration Page  
Supplies Status  
Event Log  
Usage Page  
Device Information

**Device Information**  
Device Description: HP Color LaserJet 4550  
Asset Number:  
Company Name:  
Contact Person:  
IP Address: 192.168.1.1  
Printer Model: HP Color LaserJet 4550  
Printer Number: CXXXXA  
Printer Serial Number: XXXXXXXXXX

**Other Links**  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)



# Configuring the Printer with the Device Pages

## Overview

The Device pages allow you to configure the printer from your PC. The table below lists each of the Device pages and describes its features. For more information, see the page indicated.

Device Pages	Features
Configure Printer (page 18)	Provides a list of menus that let you <i>remotely</i> print internal printer pages and configure the printer.
Alerts (page 21)	Lets you set up the printer to send problem and status alerts to anyone you choose via e-mail.
Email (page 30)	Lets you configure e-mail settings for outgoing and incoming mail.
Security (page 35)	Lets you set a password to control who can remotely cancel jobs or access the Device pages.
Other Links (page 36)	Lets you add or customize links to the web sites of your choice. These links are displayed on the left navigational bar throughout the embedded web server pages.
Device Information (page 38)	Lets you name the printer and assign an asset number to it. You can add the name of the primary contact for information about the printer. This page also shows the printer's IP address, printer model, printer number, and serial number.
Language (page 39)	Lets you select which language is used to display the embedded web server pages.

# Configure Printer

The Configure Printer page provides the capability to *remotely* print internal printer pages and configure the printer. From the internal printer pages, you can configure the paper trays and change other printer settings.

Click the menu name to display a menu and remotely manage the printer. These menus are similar to the menus that are available from your printer's control panel. (Some of the printer control panel menus are not available from the embedded web server.)

---

## Note

The HP Embedded Web Server screens shown are for the HP Color LaserJet 4550 series printer. If you are using a different printer model, you will notice slight variations in the embedded web server appearance and available features.

---

The screenshot displays the HP Embedded Web Server interface for an HP Color LaserJet 4550 printer. At the top, the HP logo and 'invent' tag are visible. The page title is 'HP Color LaserJet 4550 / 192.168.1.1'. Below the title, there are three navigation tabs: 'Home', 'Device' (which is highlighted), and 'Networking'. On the left side, there is a vertical sidebar with the following menu items: 'Configure Printer' (highlighted), 'Alerts', 'Email', 'Security', 'Other Links', 'Device Information', and 'Language'. The main content area is titled 'Configure Printer' and features a blue header 'Select A Menu'. Below this header, there are six menu options arranged in two columns: 'INFORMATION MENU', 'PAPER HANDLING MENU', and 'PRINTING MENU' on the left; and 'CONFIGURATION MENU', 'I/O MENU', and 'RESETS MENU' on the right. A blue arrow points from the text 'Select a menu name to configure items within that menu.' to the 'PAPER HANDLING MENU' link. At the bottom left of the page, there is a section titled 'Other Links' with three sub-links: 'My Printer', 'Order Supplies', and 'Solve A Problem'.

The table below describes each of the menus.

Menu Name	Description
Information Menu	This menu contains printer information pages that give details about the printer and its configuration.
Paper Handling Menu	Using this menu, you can set the type of paper in each tray.
Printing Menu	In this menu, you can select printing options, such as number of copies. You can also configure custom paper size.
Configuration Menu	Items in this menu affect the printer's behavior. For example, you can configure PowerSave and printer personality settings from this menu.
I/O Menu	Items in the I/O (input/output) Menu affect the communication between the printer and the computer.
Resets Menu	<p>Use this menu with caution. You can lose buffered page data or printer configuration settings when you select these items. Only reset the printer under the following circumstances:</p> <ul style="list-style-type: none"><li>• You want to restore the printer's default settings.</li><li>• Communication between the printer and computer has been interrupted.</li><li>• You are having problems with a port.</li></ul> <p><b>Note</b> <i>If there isn't communication between the printer and your computer, you won't be able to reset the printer.</i></p> <p>The items in the Resets Menu will clear all memory in the printer, while the Cancel Job button clears only the current job. You can access the Cancel Job button from the Security page. (For more information, see page 35.)</p> <p><b>Note</b> <i>After performing a reset you will need to configure the printer IP address.</i></p>

## Selecting Paper Size

This procedure is provided as an example. Other menu items can be set in a similar manner.

### Note

Printer drivers and software applications frequently override selections made in the Printing menu and the Paper Handling menu. For more information, see the user guide that came with your printer.

Follow the steps below to select the paper size for Tray 1:

1. Click [PAPER HANDLING MENU](#).
2. Next to TRAY 1 SIZE, select LETTER.
3. Click **Apply** to save the change.

### Note

Any changes will be reflected on the Printer Status page, the Configuration Page, and the Paper Handling menu.

The screenshot shows the HP Color LaserJet 4550 configuration page. The top navigation bar includes 'Home', 'Device', and 'Networking'. The 'Device' tab is active. The left sidebar contains 'Configure Printer', 'Alerts', 'Email', 'Security', 'Other Links', 'Device Information', and 'Language'. The main content area is titled 'Configure Printer' and 'Select A Menu'. Below this, there are links for 'INFORMATION MENU', 'PAPER HANDLING MENU', 'PRINTING MENU', 'CONFIGURATION MENU', 'I/O MENU', and 'RESETS MENU'. The 'PAPER HANDLING MENU' is selected, and a blue arrow labeled '1.' points to it. The 'PAPER HANDLING MENU' section contains a table with the following settings:

TRAY 3 SIZE	LETTER
TRAY 3 TYPE	PLAIN
TRAY 2 SIZE	A4
TRAY 2 TYPE	PLAIN
TRAY 1 SIZE	LETTER
TRAY 1 TYPE	PLAIN
TRAY 1 MODE	FIRST

A blue arrow labeled '2.' points to the 'LETTER' dropdown menu for 'TRAY 1 SIZE'. At the bottom of the page, there are 'Cancel' and 'Apply' buttons. A blue arrow labeled '3.' points to the 'Apply' button.

# Alerts

From the Alerts page, the system administrator can set up the printer to send problem and status alerts to anyone through e-mail. More than one individual can receive alerts, with each person receiving only specific alerts. For example, an administrative assistant might be responsible for keeping toner loaded in a printer or fixing paper jams, while major consumables are handled by an external service provider. Alerts can be set up so the administrative assistant gets advanced warning on toner low situations, and the external service provider gets alerts on fusers, print drums, and transfer belts.

---

## Note

For step-by-step instructions on setting up the printer to send an e-mail alert, see page 46.

---

## Note

Some of the embedded web server features require a permanent storage device (such as a hard disk) in order to set up and retain specific information on a permanent basis. This applies to the Alerts feature, as discussed below.

---

The screen below shows the Alerts page and options with a permanent storage device. With a hard disk you can set up four different lists, with up to 20 notification recipients on each of the four lists. For more information, see page 24.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device **Networking**

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Alerts

Notification Recipients

List1: [v] Edit List1  
List2: [v] Edit List2  
List3: [v] Edit List3  
List4: [v] Edit List4

Verify Email settings are valid

Security

Select Events

Events	List1	List2	List3	List4
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Apply

Opens a new window for the Email page. Here you can verify that the SMTP (Simple Mail Transfer Protocol) server is set up correctly. (Alerts will not work if the SMTP server is not set up correctly.) Exit the Email page to return to the Alerts page.

Opens a new window for the Security Page. Outgoing Mail must be selected on the Security page for alerts to work. Exit the Security page to return to the Alerts page.

Without a hard disk, there is room for only two e-mail addresses. Since there are no lists to edit, you add e-mail recipients directly on the Alerts page. The screen below shows the Alerts page without a hard disk. For more information, see page 23.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

**Configure Printer**  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

**Alerts**  
**Notification Recipients**  
Address1: name@company.com or URL  
Address2: name@company.com or URL  
Cancel Apply  
[Verify Email settings are valid](#)  
[Security](#)

**Other Links**  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

**Select Events**

Events	Address1	Address2
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Apply

The table below describes each link under **Select Events**. For more information, see “Refining Event Notification” on page 27.

Event Name	Description
Supplies	Select specific supplies, such as toner, fuser kit, or transfer kit.
Service	Select specific events that require service, such as “EIO not functional” or “Install drum kit”.
Media Path	Select events associated with the media path, such as removing a paper jam or loading a paper tray.
Advisory	Select advisory events such as “Page too complex” or “Insufficient Memory”.

# Configuring Alert Notification

## Configuring Alert Notification Without a Permanent Storage Device

### Note

These steps apply to printers without a permanent storage device (such as a hard disk).

To configure alert notification, follow the steps below:

1. Under **Notification Recipients**, enter e-mail addresses for two recipients.
2. Click the checkbox next to **Supplies, Service, Media Path, and Advisory** for each recipient you would like to receive notification. (For more information, see the table on page 22 or “Refining Event Notification” on page 27.)
3. Click **Apply** to save the information.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Alerts

Notification Recipients

Address1: name@company.com or URL

Address2: name@company.com or URL

Cancel Apply

[Verify Email settings are valid](#)

Security

Select Events

Events	Address1	Address2
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Apply

### Note

For alerts to function, Outgoing Mail must be configured. To configure Outgoing Mail, see “Email” on page 30.

After you have set up your lists, you can further refine event notification by selecting specific details and options within each event. See “Refining Event Notification” on page 27.

## Configuring Alert Notification With a Permanent Storage Device

### Note

These steps apply to printers with a permanent storage device (such as a hard disk).

To configure alert notification, follow the steps below:

1. Under **Notification Recipients**, click **Edit List1**.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Alerts  
Notification Recipients

List1: Edit List1  
List2: Edit List2  
List3: Edit List3  
List4: Edit List4

Verify Email settings are valid

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Security

Select Events

Events	List1	List2	List3	List4
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Apply

2. Under **Change List Name**, enter a name, such as Service or Supplies. (See the screen below.)

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Edit List1  
Recipient Addresses

Remove Selected Addresses

Add Recipient Address  
name@company.com

Change List Name  
Service

Cancel Apply Back

3. Under **Add Recipient Address**, enter e-mail addresses for anyone you would like to receive notification. In large environments, system administrators can route e-mail addresses to list servers or URLs for expanded notification.
4. Click **Apply** to save the information. Repeat steps 3 and 4 for each recipient address. When you have finished adding recipients, click **Back** to return to the Alerts page.

- From the Alerts page, click the checkbox next to **Supplies**, **Service**, **Media Path**, and **Advisory** for each list you would like to receive notification. (For more information, see the table on page 22 or “Refining Event Notification” on page 27.)

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Alerts  
Notification Recipients

List1: [v] Edit List1  
List2: [v] Edit List2  
List3: [v] Edit List3  
List4: [v] Edit List4

[Verify Email settings are valid](#)

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

[Security](#)

Events	List1	List2	List3	List4
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Apply

- Click **Apply** to save the information.
- Repeat steps 1-6 for each additional list.

### Note


For alerts to function, Outgoing Mail must be configured. To configure Outgoing Mail, see “Email” on page 30.

After you have set up your lists, you can further refine event notification by selecting specific details and options within each event. See “Refining Event Notification” on page 27.

## Refining Event Notification

After you have set up your lists, you can further refine event notification by selecting specific details and options within each event. (See the table on page 22 for a description of each event category.)

1. Under **Select Events**, click an event category (**Supplies**, **Service**, **Media Path**, **Advisory**) to view the events that are available.



The screenshot shows the HP Color LaserJet 4550 web interface. The top navigation bar includes 'Home', 'Device', and 'Networking'. The left sidebar contains 'Configure Printer', 'Alerts', 'Email', 'Security', 'Other Links', 'Device Information', and 'Language'. The main content area is titled 'Alerts' and 'Notification Recipients', with four lists (List1-List4) and 'Edit List' buttons. Below this is a 'Verify Email settings are valid' link and a 'Security' link. The 'Select Events' section features a table with columns for 'Events', 'List1', 'List2', 'List3', and 'List4'. The 'Events' column lists 'Supplies', 'Service', 'Media Path', and 'Advisory', each with an unchecked checkbox. 'Cancel' and 'Apply' buttons are at the bottom. A blue arrow labeled '1.' points to the 'Service' link.

Events	List1	List2	List3	List4
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

- For each event, select the lists (List 1 - 4) that you would like to be notified. (The screen below shows the Supplies events.)

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Alerts  
Select Events

Events	List1	List2	List3	List4
<a href="#">TONER LOW</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">DRUM LIFE LOW ORDER KIT</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">FUSER LIFE LOW ORDER KIT</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">TRANSFER KIT LOW ORDER KIT</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
TONER OUT	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
DRUM LIFE OUT REPLACE KIT	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
FUSER LIFE OUT REPLACE KIT	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
TRANSFER KIT OUT REPLACE KIT	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
WASTE TONER FULL REPLACE DRUM KIT	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Email Contents Apply Back


[Verify Email settings are valid](#)

[Security](#)

### Note

Those events that are hyperlinked (underlined with blue) have additional detail available.

3. After you have refined your events, click **Email Contents** to enter the information you want to include with your e-mail alert. This information may include Device Information, Contact Information, Supplies Status, Usage Page, Help Resources, Configuration Page, and an Event Log. Click the checkbox next to the information you would like to include.



4. Click **Apply** to save the information.
5. Click **Back** to return to the Alerts page.


# Email

The Email page lets you configure e-mail settings for outgoing and incoming mail. This enables you to use the printer's “send and receive” capabilities.

**Note**

For step-by-step instructions on setting up the printer to send an outgoing e-mail message, see page 46. For instructions on setting up the printer to receive an incoming e-mail message and respond with an outgoing e-mail message, see page 52.

- **Outgoing Mail** must be configured for Alerts and Email Command and Response to function.
- **Incoming Mail** must be configured for Email Command and Response to function. (You don't need to configure Incoming Mail for Alerts to function.) With Email Command and Response, you can request information from the printer, such as a configuration page or a supplies status page. For more information, see page 33.



**Note**

Settings on the Email page and the Security page work together. For outgoing and incoming mail to work properly, you need to select the appropriate check box on the Security page. (For more information, see “Security” on page 35.)

## Configuring Outgoing Mail

### Note

It is only necessary to configure Outgoing Mail if you intend to use Alerts and/or Email Command and Response. If you intend to use Email Command and Response, you must also configure Incoming Mail (see page 32).

To configure Outgoing Mail you will need the following:

- The IP address of the SMTP mail server on your network.
- The e-mail domain name suffix used for addressing e-mail messages within your organization.

### Note

Your organization's network or e-mail administrator typically provides the information required to configure Outgoing Mail.

1. Enter the SMTP Server IP address. The SMTP Server IP address is used by the printer to relay e-mail messages to other computers.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Security

Email  
Outgoing Mail

SMTP Server: [0][0][0][0] ← 1.  
Domain Name: PRINTER.DOMAIN.NAME.NOT.SET ← 2.  
Printer Email Address: printer@PRINTER.DOMAIN.NAME.NOT.SET

Incoming Mail

POP3 Server: [0][0][0][0]  
Username: printer  
Password: [ ]

Cancel Apply ← 3.

2. Enter the Domain Name. The domain name is combined with the POP3 username (or “printer” by default) in the **From:** field in e-mail messages sent from the printer. Typically, the printer's domain name will be the same as the portion of your own e-mail address after the “@” symbol. For example, if your e-mail address is “jon\_doe@hp.com”, then the printer's domain name would be “hp.com”.
3. Click **Apply** to save changes on the Email page.

### Note

For outgoing mail to work properly, you must also enable Outgoing Mail on the Security page. See page 35 for more information.

## Configuring Incoming Mail

### Note

It is only necessary to configure Incoming Mail if you intend to use Email Command and Response. You must also configure Outgoing Mail for the Email Command and Response feature to work properly (see page 31).

1. Establish a Post Office Protocol 3 (POP3) mailbox account for the printer on a mail server within your organization's network. Each POP3 account requires a username and a password. The username combined with the printer's domain name (specified in the Outgoing Mail configuration) will become the e-mail address for the printer. For example, if the POP3 mailbox account username is "printer" and the domain name is "hp.com", the printer's e-mail address will be "printer@hp.com".

### Note

Each printer that is configured for incoming mail must have its own POP3 mailbox account on your network's e-mail server.

POP3 mailbox accounts are typically configured by your organization's network or e-mail administrator.

2. Enter the IP address of the POP3 mail server and the Username and Password of the printer's mailbox account.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Security

Email  
Outgoing Mail  
SMTP Server: [0][0][0][0]  
Domain Name: PRINTER.DOMAIN.NAME.NOT.SET  
Printer Email Address: printer@PRINTER.DOMAIN.NAME.NOT.SET

Incoming Mail  
POP3 Server: [0][0][0][0]  
Username: printer  
Password: [ ]

Cancel Apply

3. Click **Apply** to save changes on the Email page.

### Note

For incoming mail to work properly, you must also enable Incoming Mail on the Security page. See page 35 for more information.

## Using Email Command and Response

When outgoing and incoming mail are configured, you can send an e-mail message to the printer requesting a configuration page or a supplies status page, and the printer will respond with an e-mail message. You can use this capability to solve a problem or check the status of printer consumables.

---

### Note

For step-by-step instructions on setting up the printer to receive an incoming e-mail message and respond with an outgoing e-mail message, see page 52.

---

### Composing a Message to the Printer

When composing a message to the printer, you must properly format the **To:**, **From:**, and **Subject:** fields in your e-mail application.


1. In the **To:** field, enter the printer's e-mail address. (To find the printer's e-mail address, from the top of the screen, click **Device**, then on the left navigational bar, click **Email**. Under **Outgoing Mail**, you should see the **Printer Email Address**.)
2. The **From:** field should be filled in automatically by your e-mail application as your return e-mail address.
3. In the **Subject:** field, using the table below, enter the type of information you would like returned (configuration page or supplies status page) and the format of the message (HTML, XML, or Text).

The table below lists the **Subject:** field entries supported:

<b>Format</b>	<b>Configuration Page</b>	<b>Supplies Status Page</b>
<b>HTML</b>	this.configpage?configpage= =email&format=html	this.configpage?suppliespage= =email&format=html
<b>XML</b>	this.configpage?configpage= =email&format=xml	this.configpage?suppliespage= =email&format=xml
<b>TEXT</b>	this.configpage?configpage= =email&format=text	this.configpage?suppliespage= =email&format=text

4. Click **Send**. (See the screen on the next page.)

The screen below shows an e-mail message to the printer requesting that a configuration page be returned in HTML format:



The printer will check for new e-mail messages once every three minutes. When the printer receives the e-mail message, it will generate a reply and send the requested information back to the sender's e-mail address (as specified in the **From:** field of the original e-mail message).

---

#### Note

Depending on delays in the network and your organization's mail server, a response may take from one minute to several hours to arrive back in your e-mail application's Inbox.

If the **To:**, **From:**, and **Subject:** fields are not properly formatted in your e-mail message, the printer will not send a message in response.

---

# Security

From the Security page, you can set a password to control who can cancel jobs remotely or access the Device pages. The username is already set as “laserjet”. Once the password has been set, users will be prompted to enter a password when they access either the Device pages or the [Order Supplies](#) link.

The screenshot shows the HP Color LaserJet 4550 Security page. The page title is "HP Color LaserJet 4550" and the URL is "HP Color LaserJet 4550". The page is divided into three tabs: Home, Device, and Networking. The Security page is currently selected. The Security page has a "Password" section with fields for Username (laserjet), New Password, and Verify Password. There are "Cancel" and "Apply" buttons. Below the Password section is the "Printer Security" section with checkboxes for "Cancel Job Button" (unchecked) and "Go Button" (checked). There is a "Cancel" button. Below the Printer Security section is the "Email Security" section with checkboxes for "Outgoing Mail" (checked) and "Incoming Mail" (unchecked). There is an "Apply" button. The "Other Links" section contains links for "My Printer", "Order Supplies", and "Solve A Problem".

**Select these checkboxes to display the Go and Cancel Job buttons on the Printer Status and Configure Printer pages.**

**Select this checkbox for Alerts and Email Command and Response to work properly.**

**Select this checkbox for Email Command and Response to work properly.**

**Opens the Email page in a new window so you can verify that the e-mail settings are correct. (Alerts and Email Command and Response will not work if the SMTP server is not set up correctly.) Exit the Email page to return to the Security page.**

**Verify Email settings are valid**

## Other Links

The Other Links page lets you add or customize links to the web sites of your choice. These links are displayed on the left navigational bar throughout the embedded web server pages.

There are three permanent links:

- [My Printer](#) connects to a set of web resources that will help you to solve specific problems and determine what additional services are available for your printer. (Detailed information including serial number, error conditions, and status will be forwarded to Hewlett-Packard's Customer Care. Hewlett-Packard will treat this information as confidential.)
- [Order Supplies](#) lets you order printer supplies over the Internet. To find out how to set a password for this page, see "Security" on page 35.
- [Solve a Problem](#) gives you access to specific printer help from HP's web site.

The three permanent links appear here, along with any user-defined links.

Any new links you add will appear here.

---

### Note

Some of the embedded web server features require a permanent storage device (such as a hard disk) in order to set up and retain specific information on a permanent basis.


With a hard disk, you can add up to five additional links; without the extra storage, you can add one additional link. (You may want to add a link to your company's web site.)

---

## Adding a Link

1. Under **Add Link**, enter the URL and the Name as you would like it to appear in the embedded web server pages.
2. Click **Add Link**.

The screen below shows the Other Links page with one user-defined URL.



The screenshot displays the HP Color LaserJet 4550 web interface. At the top left is the HP logo with the word 'invent' below it. To the right of the logo is a blue header bar containing the text 'HP Color LaserJet 4550 / 192.168.1.1' and 'HP Color LaserJet 4550'. Below the header are three tabs: 'Home', 'Device', and 'Networking'. The 'Device' tab is selected. On the left side, there is a yellow sidebar menu with the following items: 'Configure Printer', 'Alerts', 'Email', 'Security', 'Other Links', 'Device Information', and 'Language'. The 'Other Links' item is selected. Below the sidebar, there are four links: 'Other Links', 'My Printer', 'Order Supplies', 'Solve A Problem', and 'hp.com'. The main content area has a blue header bar with the text 'Other Links' and 'Add Link'. Below this is a form with two input fields: 'URL:' and 'Name:'. Below the form is an 'Add Link' button. Below the button is a blue header bar with the text 'User-defined Links'. Below this is a list of links: 'hp.com - http://www.hp.com'. Below the list is a 'Remove Selected Link' button.

## Removing a Link

1. Under **User defined Links**, select the link you would like to remove.
2. Click **Remove Selected Link**.

# Device Information

The Device Information page lets you name the printer and assign an asset number to it. You can add the name of the primary contact for information about the printer. This page also shows the printer's IP address, printer model, printer number, and serial number.

**Note**

If you make any changes on the Device Information page, click **Apply** to save those changes.

The information entered here appears on the Device Information page that can be accessed from the Home tab. It also appears in e-mail messages that are sent from the printer. This may be useful if you need to locate the printer to replace supplies or fix a problem.

The screenshot shows the HP iPrint interface for an HP Color LaserJet 4550 printer. At the top, there is a blue header with the printer's name and IP address: "HP Color LaserJet 4550 / 192.168.1.1" and "HP Color LaserJet 4550". Below the header are three tabs: "Home", "Device" (which is selected), and "Networking". On the left side, there is a vertical menu with options: "Configure Printer", "Alerts", "Email", "Security", "Other Links", "Device Information" (which is selected), and "Language". The main content area is titled "Device Information" and contains several fields: "Device Description" (filled with "HP Color LaserJet 4550"), "Asset Number" (empty), "Company Name" (empty), "Contact Person" (empty), "IP Address" (192.168.1.1), "Printer Model" (HP Color LaserJet 4550), "Printer Number" (CXXXXA), and "Printer Serial Number" (XXXXXXXXXX). At the bottom of the form are "Cancel" and "Apply" buttons. Below the menu, there is an "Other Links" section with three red links: "My Printer", "Order Supplies", and "Solve A Problem".

# Language


The Language page lets you select which language is used to display the embedded web server pages.

## Note

The default language is the language currently in use by the web browser. If your browser and printer control panel both use a language that is not available for the embedded web server, English will be selected as the default.

The following languages are available:

- English
- Italian
- Spanish
- Danish
- Swedish
- French
- German
- Portuguese
- Dutch
- Finnish
- Norwegian



If you make any changes on the Language page, click **Apply** to save your changes.

## Caution

Choosing a setting other than “View Pages in Browser Language” (the default) will change the language for everyone browsing the embedded web server.



# Managing the Network with the Networking Pages

## Overview

The Networking pages allow you to view network status and configure the printer's network card from your PC. The Networking pages are not part of the embedded web server in your printer; they reside on an embedded web server that is included with your HP JetDirect EIO network card.

The appearance and features of the Networking pages will differ, depending on the version of your HP JetDirect card. The following screen is similar to what you might see when you click **Networking**. From the left navigational bar, click the Networking page that you want to view. (The Network Settings page is shown below.)

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device **Networking**

Configuration  
TCP/IP IPX/SPX AppleTalk DLC/LLC SNMP

Network Settings  
Select a Language  
Support Info  
Other Settings

Security  
Admin Password  
Access Control

Diagnostics  
Network Statistics  
Protocol Info  
Test Page  
Refresh Rate

Other Links  
[Help](#)  
[Support](#)  
[HP Home](#)

IP Configuration Method: BOOTP

Note: A change in IP Address will result in loss of connectivity to the browser.

Manual

Host Name: HP Color LaserJet 4550

IP Address: 192.168.1.1

Subnet Mask: 255.255.248.0

Default Gateway: 192.168.1.1

Domain Name:

Primary WINS Server:

Secondary WINS Server:

Syslog Server:

Syslog Maximum Messages: 10

Syslog Priority: 8

Idle Timeout: 90

TTL/SLP: 4

System Contact:

System Location:

Banner Page:

Apply Cancel

Below are some of the tasks you may be able to perform from the Networking pages:

- Change network configuration settings for various types of network connections.
- Enable or disable printing protocols.
- Set up a support contact and support URLs.
- Set up a password to control who can remotely access the Networking pages.
- View general network status information, including network statistics stored on the print server.
- View protocol information for all supported network connections.
- Display the HP JetDirect Configuration Page.
- Set the frequency at which the embedded web server will check the network status.

For more information about the Networking pages, refer to the following:

- **Help**—On each Networking page, under **Other Links** there is a Help link that provides a description of the networking features and helpful tips for using them. Also, from the Help page you can access additional help from HP's web site. **Other Links**
  - [Help](#)
  - [Support](#)
  - [HP Home](#)
- **HP JetDirect Print Server Administrator's Guide**—This guide may be available on the software CD that shipped with your printer. To download the most recent version of the guide, go to: [http://www.hp.com/support/net\\_printing](http://www.hp.com/support/net_printing).

# Appendix A – HP Web JetAdmin and the HP Embedded Web Server

## How does HP Web JetAdmin work together with the HP Embedded Web Server?

HP's Web JetAdmin is a web-based system management tool that provides efficient installation and management of networked peripherals from a web browser. It allows network administrators to manage their network printers from virtually anywhere.

The HP Embedded Web Server and Web JetAdmin work together to meet all your printer management needs.

The HP Embedded Web Server provides a simple, easy-to-use solution for one-to-one printer management in environments with a limited number of printers. However, environments with several printers may want to use HP Web JetAdmin for group printer management. With HP Web JetAdmin you can discover, manage, and configure multiple devices simultaneously.

HP Web JetAdmin is available from HP Customer Care Online ([http://www.hp.com/support/net\\_printing](http://www.hp.com/support/net_printing)).



# Appendix B – How Do I?

## Sharing Printer Information

### How can I share my printer information without setting up e-mail alerts?

Your web browser has a feature that is useful for sharing printer information.

1. Browse to the embedded web server page that you want to share.
2. Follow the instructions below for your browser:
  - *For Microsoft Internet Explorer:* From the **File** menu, click **Send**, then click **Page by E-mail**.
  - *For Netscape Navigator:* From the **File** menu, click **Send Page**.

An e-mail composition window will appear, with the selected embedded web server page attached. You can send the e-mail to anyone you wish.


For example, you might want to send the Configuration Page to HP Customer Care to help troubleshoot a printer problem.

# Setting Up the Printer to Send E-mail Messages

## How do I set up the embedded web server so that the printer can send an outgoing e-mail message?


The following example shows how to configure the HP Color LaserJet 4550 printer to send you an e-mail alert anytime a printer door or cover has been left open.

1. Launch your web browser.
2. In the **Address:** or **Go to:** field, type the IP address assigned to the printer (for example: `http://192.168.1.1`) or the host name (for example: `http://myprinter`).



(If you do not know the IP address for the printer, see page 7.)

3. The embedded web server Home page should appear. From the top of the screen, click **Device**, then on the left navigational bar, click **Alerts**.




4. Add your e-mail address (follow the appropriate instructions below).

### If the Printer has a Permanent Storage Device


#### Note

These steps apply to printers with a permanent storage device (such as a hard disk).

- a. Under **Notification Recipients**, click **Edit List1**.



- b. Under **Add Recipient Address**, enter your e-mail address. (For example: “name@company.com”).



- c. Click **Apply**.
- d. Click **Back** to return to the Alerts page.

## If the Printer DOES NOT have a Permanent Storage Device

### Note

These steps apply to printers without a permanent storage device (such as a hard disk).

- a. Under **Notification Recipients**, enter your e-mail address. (For example: “name@company.com”.)

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

**Alerts**  
**Notification Recipients**

Address1: name@company.com  
Address2:

Cancel Apply

[Verify Email settings are valid](#)

- b. Click **Apply**.

5. Under **Select Events**, click **Media Path**.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

**Alerts**  
**Notification Recipients**

List1:  Edit List1  
List2:  Edit List2  
List3:  Edit List3  
List4:  Edit List4

[Verify Email settings are valid](#)

**Other Links**  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

[Security](#)

**Select Events**

Events	List1	List2	List3	List4
<a href="#">Supplies</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Service</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Media Path</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">Advisory</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Cancel Apply

6. Select the **List1** checkbox next to CLOSE DRAWERS/DOORS/COVERS.

The screenshot shows the HP Color LaserJet 4550 web interface. The top navigation bar includes 'Home', 'Device', and 'Networking'. The left sidebar contains 'Configure Printer', 'Alerts', 'Email', 'Security', 'Other Links', 'Device Information', and 'Language'. The main content area is titled 'Alerts' and 'Select Events'. A table lists various events with checkboxes for List1, List2, List3, and List4. The 'CLOSE DRAWERS/DOORS/COVERS' event has its List1 checkbox checked, indicated by a blue arrow and the number '6.'. Below the table are buttons for 'Cancel', 'Email Contents', 'Apply', and 'Back'. At the bottom, there are links for 'Verify Email settings are valid' and 'Security'.

Events	List1	List2	List3	List4
<a href="#">REMOVE PAPER JAM</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">CLOSE DRAWERS/DOORS/COVERS</a>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">INSTALL TRAY</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">TRAY OPEN</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">TRAY LOAD</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
<a href="#">MANUALLY FEED</a>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

7. Click **Apply**. The following screen should appear. Click **OK**.

**Success**

Your selections have been accepted.

**Warning**

SMTP Server: Not a valid address Verify Email settings are valid

- On the left navigational bar, click **Email**.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device **Networking**

**Email**

Outgoing Mail

SMTP Server: [ ] . [ ] . [ ] . [ ] ← 9.

Domain Name: [PRINTER.DOMAIN.NAME.NOT.SET] ← 10.

Printer Email Address: printer@PRINTER.DOMAIN.NAME.NOT.SET

Incoming Mail

POP3 Server: [ ] . [ ] . [ ] . [ ]

Username: [printer]

Password: [ ]

Cancel Apply ← 11.

← 12. [Security](#)

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

### Note

Your organization's network or e-mail administrator typically provides the information required to configure outgoing mail. See page 31 for more information.

- Under **Outgoing Mail**, enter the SMTP Server IP address.
- Under **Outgoing Mail**, enter the Domain Name.
- Click **Apply**.
- Click [Security](#).
- Under **Security**, select the **Outgoing Mail** checkbox.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device **Networking**

**Security**

Password

Username laserjet

New Password [ ]

Verify Password [ ]

Cancel Apply

**Security**

Printer Security

Cancel Job Button

Go Button

Cancel

← 13. → **Email Security**

Outgoing Mail

Incoming Mail

← 14. → Apply

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

[Verify Email settings are valid](#)

- Click **Apply**.

15. To test the configuration, open the top cover of the printer, then go to your computer and verify that you have received an e-mail message from the printer. (See the example below.)

**From:** printer@hp.com [[mailto: printer@hp.com](mailto:printer@hp.com)]  
**Sent:** Tuesday, December 12, 2000 8:45 AM  
**To:** name@company.com  
**Subject:** Event:CLOSE DRAWERS/DOORS/COVERS

HP Device Alert:  
Event:CLOSE DRAWERS/DOORS/COVERS  
Device Identification:  
Description: HP Color LaserJet 4550  
IP Address: 192.168.1.1  
Printer Model: HP Color LaserJet 4550  
Model\_Number: CXXXXXA  
Printer Serial Number: XXXXXXXXXXXXA  
Asset Number:

Help Resources:  
The printer control panel displayed the following information:  
CLOSE TOP COVER

Detailed device information is available at: <http://192.168.1.1>  
Additional resources are available at:  
Solve A Problem : [http://www.hp.com/support/lj4550\\_solve\\_a\\_problem](http://www.hp.com/support/lj4550_solve_a_problem)

Contact Information:  
Company Name:  
Contact Person: Support Person


Device\_Alert\_Version:1.0

# Setting Up the Printer to Receive and Respond to E-mail Messages

**How do I set up the embedded web server so that the printer can receive an incoming e-mail message and respond with an outgoing e-mail message?**


The following example shows how to configure the HP Color LaserJet 4550 printer so that you can send an e-mail message to the printer, requesting a configuration page, and the printer will respond with an e-mail message.

1. Launch your web browser.
2. In the **Address:** or **Go to:** field, type the IP address assigned to the printer (for example: `http://192.168.1.1`) or the host name (for example: `http://myprinter`).



(If you do not know the IP address for the printer, see page 7.)

3. The embedded web server Home page should appear. From the top of the screen, click **Device**, then on the left navigational bar, click **Email**.



## Note

Your organization's network or e-mail administrator typically provides the information required to configure outgoing and incoming mail. See pages 31-32 for more information.

4. Under **Outgoing Mail**, enter the SMTP Server IP address.

HP Color LaserJet 4550 / 192.168.1.1  
HP Color LaserJet 4550

Home Device Networking

Configure Printer  
Alerts  
Email  
Security  
Other Links  
Device Information  
Language

Other Links  
[My Printer](#)  
[Order Supplies](#)  
[Solve A Problem](#)

Cancel

Apply

Security

Outgoing Mail

SMTP Server: [0][0][0][0] ← 4.  
Domain Name: [PRINTER.DOMAIN.NAME.NOT.SET] ← 5.  
Printer Email Address: printer@PRINTER.DOMAIN.NAME.NOT.SET

Incoming Mail


POP3 Server: [0][0][0][0] ← 6.  
Username: [printer] ← 7.  
Password: [ ]

8. → Apply

9. → Security


5. Under **Outgoing Mail**, enter the Domain Name.
6. Under **Incoming Mail**, enter the POP3 Server IP address.
7. Under **Incoming Mail**, enter the Username of the printer's mailbox account (for example, "printer").
8. Click **Apply**.
9. Click [Security](#).

- Under **Security**, select the **Outgoing Mail** and **Incoming Mail** checkboxes.



- Click **Apply**.
- From your e-mail application, compose a message to the printer, following the steps below:
  - In the **To:** field, enter the printer’s e-mail address. (To find the printer’s e-mail address, from the top of the screen, click **Device**, then on the left navigational bar, click **Email**. Under **Outgoing Mail**, you should see the **Printer Email Address**.)
  - The **From:** field should be filled in automatically by your e-mail application as your return e-mail address.
  - In the **Subject:** field, enter:
 

“this.configpage?configpage=email&format=html”



**Note**

For more information about composing a message to the printer, see page 33.

- Click **Send**.

14. You should receive an e-mail from the printer in your e-mail application's Inbox. (See the screen below.)

---

### Note

Depending on delays in the network and your organization's mail server, a response may take from one minute to several hours to arrive back in your e-mail application's Inbox.

If the **To:**, **From:**, and **Subject:** fields are not properly formatted in your e-mail message, the printer will not send a message in response.

---

### Configuration Page

#### Printer Information

Firmware Datecode: 1.0  
Jam Recovery: OFF  
Print PS Errors: OFF  
Page Count: 852  
Color Page Count: 75  
Product Name: HP Color LaserJet 4550  
Printer Name: HP Color LaserJet 4550  
Printer Number: CXXXXA  
Resolution: 600  
Printer Serial Number: XXXXXXXXXXXX  
HP JetSend Address: 192 .168 . 1 . 1

#### Installed Personalities and Options

PCL (20000828)  
PCLXL (20000828)  
PS (20000828)  
DIMM Slot 1: Side 1 : 64 MB SDRAM  
DIMM Slot 1: Side 2: Empty  
DIMM Slot 3: Side 1 : 16 MB ROM  
DIMM Slot 3: Side 2 : 0 MB SDRAM  
EIO 1: HP JetDirect J4169A  
EIO 2: HP C2985B  
DISK Storage: 3102 MB Capacity

#### Security

Control Panel Lock: DISABLED  
Control Panel Password: DISABLED  
Device Type: DISK Write Protect: DISABLED

#### Memory

Total Memory: 64 MB  
DWS: 24.93

#### Paper Trays and Options

Mopier: ON  
Default Paper Size: LETTER  
Tray 1 (LETTER)  
Tray 2 (LETTER)  
Tray 3 (LETTER)  
Input Trays:  
1: TRAY 1, 150 Sheets  
2: TRAY 2, 250 Sheets  
3: TRAY 3, 500 Sheets  
Output Bins:  
1: STANDARD, 250 Sheets, Face Down

#### Density Settings

Black: 0  
Cyan: 0  
Magenta: 0  
Yellow: 0



# Index

- accessories, status, 10, 11
- Alerts, 21
  - configure notification, 23, 24
  - refine notification, 27
  - setting up, 46
- asset number, 15
  
- browser, required, 7
  
- Calibration Menu, 18
- Cancel Job button, 10, 35
- ChaiVM, 4
- company name, 15
- Configuration Menu, 18
- Configuration Page, 11
- configuration page,
  - printing, 6, 7
- Configure Printer, 18
- consumables
  - ordering, 36
  - status, 10
- contact person, 15, 38
- control panel
  - security, 11
  - status, 10
  
- density settings, 11
- Device Information page, 15, 38
- Device pages, 8, 17–40
- DIMMs
  - ordering, 36
  - status, 10, 11
- drum kit
  - ordering, 36
  - status, 10, 12
  
- duplex print jobs, 14
- DWS, 11
  
- EIO card
  - ordering, 36
  - status, 11, 41–42
- e-mail
  - alerts, 21
  - embedded web server
    - page, 45
    - setting up incoming and outgoing, 52
    - setting up outgoing, 46
- Email page, 30
  - Command and Response, 30
  - incoming mail, 32
  - outgoing mail, 31
  - setting up mail server, 30, 33
- embedded virtual machine, 4
- embedded web server, 3
  - accessing, 7
  - features, 5
  - navigating, 8
- error messages, 13
- Event Log, 13
  
- firewall, 7
- firmware datecode, 11
- fuser kit
  - ordering, 36
  - status, 10, 12

- Go button, 10, 35
- group printer management, 43
- hard disk, 6, 10
  - capabilities with, 22
  - ordering, 6, 36
- help, 10, 36
  - network, 42
- Home pages, 8, 9–15
- host name, 7, 46, 52
- HP JetDirect card, 41–42
- HP JetDirect Print Server Administrator's Guide*, 42
- I/O Menu, 18
- Information Menu, 18
- IP address, 7, 11, 15, 46, 52
- IP-based network, 7
- IPX-based network, 7
- jam recovery, 11
- Java™ applications, 4
- Job Cancel button, 10, 35
- Language page, 39
- languages, 39. *See also printer languages*
- lights, 10
- links, 36
- maintenance kits
  - ordering, 36
  - status, 10, 12
- media
  - ordering, 36
  - status, 10
- memory
  - ordering, 36
  - status, 10, 11
- menus, 18
- messages
  - control panel, 10
  - error, 13
- model number, 11
- mopier configuration, 11
- network
  - address, 11, 15
  - required, 7
  - status, 41–42
- Networking pages, 8, 41–42
- one-sided print jobs, 14
- online help, 10, 36
  - network, 42
- operating system, 7
- ordering
  - additional storage, 6
  - supplies, 36
- Other Links page, 36
- output bin, 10, 11
- page count, 11, 12, 14
- page sizes printed, 14
- Paper Handling Menu, 18
- paper trays, 10, 11
- parallel connection, 7
- part number
  - printer, 38
  - supplies, 12
- password, create, 35
- PCL, 11
- personalities, installed, 11
- PJL storage, 10
- print PS errors, 11
- printer
  - configuration, 10
  - description, 15
  - information, 11, 15
  - languages, installed, 11
  - menus, 18
  - model, 15
  - name, 11, 14
  - number, 11, 15
  - settings, 18
- Printer Status, 10
- Printing Menu, 18

- Private/Stored Jobs Menu, 18
- problem
  - alerts, 21
  - solving, 36
- PS, 11

- Quick Copy Jobs Menu, 18

- RAM DISK storage, 10, 11
- recycle toner cartridge, 12
- refresh rate, 10
  - network, 42
- Resets Menu, 18
- resolution, 11

- security, 11
- Security page, 35
- serial number, 11, 12, 14, 15
- share printer information, 45
- simplex print jobs, 14
- sizes printed, 14
- status, 10, 12
  - alerts, 21
  - network, 41–42

- supplies
  - ordering, 36
  - status, 10, 12
- Supplies Status page, 12
- system requirements, 7

- toner cartridge
  - alerts, 21
  - recycling, 12
  - status, 10, 12
- toner coverage, 14
- total pages printed, 14
- transfer kit
  - ordering, 36
  - status, 10, 12
- trays, 10, 11
- two-sided print jobs, 14

- Usage Page, 14

- virtual machine, 4

- web browser, required, 7
- Web JetAdmin, 43
- write protection, 11