


ThinkCentre

Hardware Replacement Guide
Types 8009, 8791, 8795, 8799
Types 8803, 8807, 8812



ThinkCentre

Hardware Replacement Guide
Types 8009, 8791, 8795, 8799
Types 8803, 8807, 8812

First Edition (June 2006)

© Copyright Lenovo 2005, 2006.

Portions © Copyright International Business Machines Corporation 2005.

All rights reserved.

U.S. GOVERNMENT USERS – RESTRICTED RIGHTS: Our products and/or services are provided with RESTRICTED RIGHTS. Use, duplication or disclosure by the Government is subject to the GSA ADP Schedule contract with Lenovo Group Limited, if any, or the standard terms of this commercial license, or if the agency is unable to accept this Program under these terms, then we provide this Program under the provisions set forth in Commercial Computer Software–Restricted Rights at FAR 52.227-19, when applicable, or under Rights in Data-General, FAR 52.227.14 (Alternate III).

Contents

Overview	v
Safety information for customers	v
Safety information for service personnel	v
Additional information resources	vi
Tools required	vi
Handling static-sensitive devices	vi
Chapter 1. Locations	1
Locating the connectors on the front of your computer	1
Locating the connectors on the rear of your computer	2
Locating components	3
Identifying parts on the system board	4
Chapter 2. Replacing hardware	5
Opening the cover	5
Replacing the power supply	6
Replacing the system board	9

Replacing the microprocessor	14
Replacing the hard disk drive	19
Replacing the optical drive	22
Replacing a memory module	25
Replacing a PCI adapter	27
Replacing the system fan	29
Replacing the rear fan bracket assembly	31
Replacing the internal speaker	33
Replacing a keyboard	35
Replacing a mouse	36
Completing the parts replacement	37
Updating (flashing) BIOS from a diskette or CD-ROM	38

Appendix. Notices	39
Television output notice	40
Trademarks	40

Overview

This guide is intended to be used by customers who are replacing Customer Replaceable Units (CRUs) as well as trained service personnel who are replacing Field Replaceable Units (FRUs). In this document, CRUs and FRUs will be referred to as parts.

Note: Trained service personnel should refer to the *Hardware Maintenance Manual* for parts ordering information.

This guide does not include procedures for all parts. It is expected that cables, switches, and certain mechanical parts can be replaced by trained service personnel without the need for step-by-step procedures.

This guide contains instructions for replacing the following parts:

Note: Use only parts provided by Lenovo™.

- Power supply
- System board
- Microprocessor
- Hard disk drive
- Optical drive
- Memory module
- PCI adapter card
- System fan
- Rear fan bracket assembly
- Internal speaker
- Keyboard
- Mouse

Safety information for customers

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer. To obtain a copy of the *Safety and Warranty Guide* go to the World Wide Web at <http://www.lenovo.com/support/>.

Safety information for service personnel

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain a copy of the *HMM*, go to the World Wide Web at <http://www.lenovo.com/support/>.

Additional information resources

If you have Internet access, the most up-to-date information for your computer is available from the World Wide Web.

You can find the following information:

- CRU removal and installation instructions
- CRU removal and installation videos
- Publications
- Troubleshooting information
- Parts information
- Downloads and drivers
- Links to other useful sources of information
- Support phone list

To access this information, point your browser to <http://www.lenovo.com/support/>.

Tools required

To replace some parts in your computer, you might need a flat-blade or Phillips screwdriver.

Handling static-sensitive devices

Static electricity, although harmless to you, can seriously damage computer components and parts.

When replacing a part, do *not* open the static-protective package containing the new part until the defective part has been removed from the computer and you are ready to install the new part.

When you handle parts and other computer components, take these precautions to avoid static-electricity damage:


- Limit your movement. Movement can cause static electricity to build up around you.
- Always handle parts and other computer components carefully. Handle adapters, memory modules, system boards, and microprocessors by the edges. Never touch any exposed circuitry.
- Prevent others from touching the parts and other computer components.
- Before you replace a new part, touch the static-protective package containing the part to a metal expansion-slot cover or other unpainted metal surface on the computer for at least two seconds. This reduces static electricity in the package and your body.
- When possible, remove the new part from the static-protective packaging and install it directly in the computer without setting the part down. When this is not possible, place the static-protective package that the part came in on a smooth, level surface and place the part on it.
- Do not place the part on the computer cover or other metal surface.

Chapter 1. Locations

This chapter provides illustrations to help locate the various connectors, controls and components of the computer. To open the computer cover, see “Opening the cover” on page 5.

Locating the connectors on the front of your computer

The following illustration shows the location of connectors on the front of the computer.




- 1** Headphone connector
- 2** Microphone connector

- 3** USB connector
- 4** USB connector

Locating the connectors on the rear of your computer


The following illustration shows the location of connectors on the rear of the computer.



- | | | | |
|----------|-----------------------|-----------|------------------------------|
| 1 | PCI adapter connector | 8 | Ethernet connector |
| 2 | Integrated cable lock | 9 | USB connectors |
| 3 | USB connector | 10 | USB connectors |
| 4 | USB connector | 11 | Audio line out connector |
| 5 | VGA monitor connector | 12 | Audio line in connector |
| 6 | Parallel connector | 13 | Power supply diagnostic LEDs |
| 7 | Serial connector | 14 | Power connector |

Locating components

The following illustration will help you locate the various components in your computer.




- | | | | |
|----------|----------------------------|----------|---------------------------|
| 1 | PCI riser | 6 | System fan |
| 2 | Power supply assembly | 7 | Internal speaker |
| 3 | Optical drive eject button | 8 | Cable clip |
| 4 | Optical drive | 9 | Rear fan bracket assembly |
| 5 | Hard disk drive | | |

Identifying parts on the system board

The system board (sometimes called the planar or motherboard) is the main circuit board in your computer. It provides basic computer functions and supports a variety of devices.

The following illustration shows the locations of parts on the system board.



- | | | | |
|----------|-------------------------|-----------|------------------------------|
| 1 | Battery | 10 | Internal speaker connector |
| 2 | SATA connector | 11 | Memory connector 1 |
| 3 | Optical drive connector | 12 | Memory connector 2 |
| 4 | PCI riser connector | 13 | Microprocessor fan connector |
| 5 | Front panel connector | 14 | Clear CMOS/Recovery jumper |
| 6 | 12v power connector | 15 | Temperature sensor connector |
| 7 | Power connector | 16 | Rear fan connector |
| 8 | System fan connector | 17 | Cover presence switch |
| 9 | Microprocessor | | |

Note: Your computer has support for two double data rate 2 (DDR2) dual inline memory modules (DIMMs).

Chapter 2. Replacing hardware

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual* (HMM) for the computer. To obtain copies of the *Safety and Warranty Guide* or HMM, go to <http://www.lenovo.com/support/>.

Note: Use only parts provided by Lenovo.

Opening the cover

Important




Turn off your computer and wait 3 to 5 minutes to let the computer cool before opening the computer cover.

To open the computer cover:

1. Remove any media (diskettes, CDs, or tapes) from the drives, shut down your operating system, turn off all attached devices, and the computer.
2. Unplug all power cords from electrical outlets.
3. Disconnect all cables attached to the computer. This includes power cords, input/output (I/O) cables, and any other cables that are connected to the computer.
4. Remove any locking devices such as a Kensington lock that secure the cover.

5. Press the buttons on the sides of the computer and pivot the cover upward to open the computer as shown.




Replacing the power supply

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.


This section provides instructions on how to replace the power supply.

1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the power supply.




3. Remove the PCI riser. See “Replacing a PCI adapter” on page 27.

4. Remove the three screws at the rear of the chassis securing the power supply.




5. Disconnect the power supply cables from the system board connectors **1** and **2** and from all drives.



6. Disconnect the power supply cables from all the drives.

7. Remove the power supply assembly from the computer.



8. Install the new power supply assembly into the chassis so that the screw holes in the power supply assembly align with those in the chassis.

Note: Use only the screws that are provided by Lenovo.

9. Install and tighten the three screws at the rear of the chassis to secure the power supply assembly.
10. Reconnect all the power supply cables to the drives and the system board.
11. Reinstall the PCI riser.
12. Go to “Completing the parts replacement” on page 37.


Replacing the system board

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace the system board.


1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the system board.




3. Remove the PCI riser. See “Replacing a PCI adapter” on page 27.
4. Locate the rear fan bracket assembly and the rear fan connector. See “Locating components” on page 3 and “Identifying parts on the system board” on page 4.
5. Disconnect the rear fan cable and remove the rear fan bracket assembly by lifting it off the system board.
6. Take note of the location of all cable connections on the system board. It will be necessary to reconnect them properly when installing a new system board.
7. Disconnect all cables connected to the system board. See “Identifying parts on the system board” on page 4.
8. Take note of the location of the memory modules and remove them from the failing system board. See “Replacing a memory module” on page 25.

9. Remove the heat sink **1** from the system board by pivoting the lever **2** securing the heat sink until it is fully in the up position. Lift the heat sink off of the system board.

Note: Place the heat sink on its side on a clean, flat surface so the thermal interface on the bottom of the heat sink does not touch the surface and become contaminated.




10. Use the handle at the rear of the system board to pull the system board and tray out the rear of the chassis.




11. Place the failing system board next to the new system board on a clean, flat surface.

12. To remove the microprocessor from the failing system board, release the lever **1** securing the microprocessor **2** then pivot the microprocessor retainer **1** until it is fully open.




13. Remove the microprocessor from the system board socket by lifting it out of the socket.



Important

Do not touch the gold contacts on the bottom of the microprocessor. If you must touch the microprocessor, touch only the sides.

- a. Take notice of the orientation of the notches **1** on the microprocessor. This is important when installing the microprocessor on the new system board.




- b. Do not drop anything on the socket while it is open. Keep all contacts as clean as possible.
14. On the new system board, release the lever securing the microprocessor retainer then pivot the retainer until it is fully open.
15. Position the microprocessor so that the notches on the microprocessor are aligned with the tabs in the microprocessor socket.


Important

To avoid damaging the microprocessor contacts, do not tilt the microprocessor when installing it into the socket.

16. Lower the microprocessor straight down into the system board socket of the new system board.




17. Lower the microprocessor retainer **1** and then lower the lever **3** to secure the retainer. Make sure the lever is securely locked into position.



Note: There will be a black plastic cover on the microprocessor retainer to protect the socket on the new system board. When you lock the microprocessor in position, remove the black plastic cover. Place the black plastic cover on the microprocessor retainer of the failing system board.

18. Install the new system board and tray into the rear of the chassis until it is fully seated.
19. Place the heat sink **1** into position and lower the lever **2** to secure the heat sink.



20. Reinstall the memory modules on the new system board in the same location as they were on the failing system board. See “Replacing a memory module” on page 25.
21. Reconnect all cables that were disconnected from the system board. See “Identifying parts on the system board” on page 4.
22. Reinstall the PCI riser that was removed. See “Replacing a PCI adapter” on page 27.
23. Reinstall the rear fan bracket assembly and connect the fan cable to the system board.
24. Go to “Completing the parts replacement” on page 37.

Replacing the microprocessor

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

When you receive a new microprocessor, you also receive a new heat sink. You must use the new heat sink with the new microprocessor. If you use the old heat sink with the new microprocessor, your computer might over heat and could cause intermittent problems.

Important


Touch only the sides of the microprocessor. Do not touch the gold contacts on the bottom.

This section provides instructions on how to replace the microprocessor.


Important

Leave your computer turned off for at least one hour before removing the microprocessor to allow the thermal interface between the microprocessor and the heat sink time to cool down.


1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the system board.




3. Locate the microprocessor fan connector on the system board. See “Identifying parts on the system board” on page 4.
4. Disconnect the microprocessor fan cable from the system board.
5. Remove the heat sink **1** from the system board by pivoting the lever **2** securing the heat sink until it is fully in the up position. Lift the heat sink off of the system board.



6. Release the lever **3** securing the microprocessor **2** then pivot the microprocessor retainer **1** until it is fully open.




7. Remove the microprocessor from the system board socket by lifting it out of the socket.



Important


Do not touch the gold contacts on the bottom of the microprocessor. Touch only the sides.

- a. Take notice of the orientation of the notches **1** on the microprocessor. This is important when reinstalling the microprocessor on the system board.



- b. Do not drop anything on the socket while it is open. Keep all contacts as clean as possible.
8. Make sure that the lever on the microprocessor retainer is fully open.

9. Loosen the black cover **2** that protects the gold contacts on the microprocessor **1**, but do not remove it. Pick up the new microprocessor then completely remove the black cover. Place the black cover on the old microprocessor.




10. Position the microprocessor so that the notches on the microprocessor are aligned with the tabs in the microprocessor socket.


Important

To avoid damaging the microprocessor contacts, do not tilt the microprocessor when installing it into the socket.


11. Lower the microprocessor straight down into the system board socket.



12. Lower the microprocessor retainer **1** and then lower the lever **3** to secure the retainer. Make sure the lever is securely locked into position.



13. Place the new heat sink **1** into position and lower the lever **2** to secure the heat sink.



14. Reconnect the microprocessor fan cable to the system board.
15. Go to “Completing the parts replacement” on page 37.

Replacing the hard disk drive

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace the hard disk drive.


Important

When you receive a new hard disk drive, you also receive a set of *Product Recovery CDs*. The set of *Product Recovery CDs* will enable you to restore the contents of the hard disk to the same state as when your computer was originally shipped from the factory. For more information on recovering factory-installed software, refer to “Recovering software” in your *Quick Reference*.

To replace a hard disk drive, do the following:


1. Open the computer cover. See “Opening the cover” on page 5.

2. Pivot the drive bay assembly upward to gain access to the hard disk drive.




3. Disconnect the signal and power cables from the rear of the hard disk drive.

4. Lift the hard disk drive and bracket up to remove it from the hard drive bay.



5. Remove the failing hard disk drive from the blue bracket by flexing the bracket enough to slide the drive out.

6. To install the new hard disk drive into the blue bracket, flex the bracket and align the pins **1** through **4** on the bracket with the holes in the hard disk drive. Do not touch the circuit board **5** on the bottom of the hard disk drive.



7. Insert the new hard disk drive into the hard drive bay until it snaps into position.
8. Connect the signal and power cables to the rear of the hard disk drive.
9. Go to “Completing the parts replacement” on page 37.

Replacing the optical drive


Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.


This section provides instructions on how to replace an optical drive.

1. Open the computer cover. See “Opening the cover” on page 5.


2. Push the optical drive eject button.




3. Pull the eject bar.



4. Slide the optical drive out of the front of the computer.



5. Slide the new optical drive into the bay until it locks into position.



6. Go to "Completing the parts replacement" on page 37.

Replacing a memory module


Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace a memory module.


Note: Your computer has support for two memory modules.

1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the system board.




3. Remove any parts that might prevent access to the memory connectors.

4. Remove the memory module being replaced by opening the retaining clips as shown.



5. Position the replacement memory module over the memory connector. Make sure that the notch **1** on the memory module aligns correctly with the connector key **2** on the system board. Push the memory module straight down into the memory connector until the retaining clips close.



6. Go to "Completing the parts replacement" on page 37.


Replacing a PCI adapter

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.


This section provides instructions on how to replace a PCI adapter.

1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the system board.




3. Locate the cable clip. See “Locating components” on page 3.
4. Remove all cables from the cable clip attached to the PCI riser.

5. Pull upward on the blue handle **1** to remove the PCI riser from the computer.



6. Pivot the adapter latch upward and remove the failing adapter.
7. Remove the new adapter from its static-protective package.
8. Install the new adapter into the expansion connector in the PCI riser.



9. Pivot the adapter latch down to retain the adapter.
10. Reinstall the PCI riser into the system board.
11. Go to “Completing the parts replacement” on page 37.


Replacing the system fan

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace the system fan.


1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the system fan.



3. Locate the system fan. See “Locating components” on page 3.
4. Disconnect the system fan cable from the system board. See “Identifying parts on the system board” on page 4.

Note: Make sure you note the location of the system fan cable when you disconnect it from the system board.

5. Press the tab at the top front of the system fan.
6. Remove the system fan **1** by sliding the tabs out of the side slots and lifting out.



7. Install the new system fan and connect the system fan cable to the system board.
8. Go to “Completing the parts replacement” on page 37


Replacing the rear fan bracket assembly

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace the rear fan bracket assembly.

1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the rear fan bracket assembly.




3. Locate the rear fan bracket assembly. See “Locating components” on page 3.

4. Disconnect the rear fan cable from the system board. See “Identifying parts on the system board” on page 4.

Note: Make sure you note the location of the rear fan cable when you disconnect it from the system board.

5. Lift the rear fan bracket assembly out of the slots **1**.



6. Install the new rear fan bracket assembly and connect the rear fan cable to the system board.
7. Go to “Completing the parts replacement” on page 37.


Replacing the internal speaker

Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace the internal speaker.


1. Open the computer cover. See “Opening the cover” on page 5.
2. Pivot the drive bay assembly upward to gain access to the speaker connector.



3. Locate the speaker connector on the system board. See “Identifying parts on the system board” on page 4.
4. Disconnect the speaker cable from the system board.

5. Push downward on the metal tab shown while lifting the speaker out from the computer.

Note: You might need a flat-blade screwdriver to gently pry the speaker from the metal tabs that secure it.



6. Position the bottom of the new speaker into the metal tabs then pivot the top of the speaker downward until it snaps into position.
7. Connect the speaker cable to the system board. See “Identifying parts on the system board” on page 4.
8. Go to “Completing the parts replacement” on page 37.

Replacing a keyboard


Attention

Do not open your computer or attempt any repair before reading the “Important safety information” in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace a keyboard.

1. Remove any media (diskettes, CDs, or tapes) from the drives, shut down your operating system, and turn off all attached devices.
2. Unplug all power cords from electrical outlets.
3. Locate the keyboard connector.

Note: Your keyboard may be connected to a USB connector. Depending on where your keyboard is connected, see “Locating the connectors on the rear of your computer” on page 2 or “Locating the connectors on the front of your computer” on page 1.



4. Disconnect the failing keyboard cable from the computer.
5. Connect the new keyboard to the appropriate connector on the computer.
6. Go to “Completing the parts replacement” on page 37.

Replacing a mouse


Attention

Do not open your computer or attempt any repair before reading the "Important safety information" in the *Safety and Warranty Guide* that was included with your computer or in the *Hardware Maintenance Manual (HMM)* for the computer. To obtain copies of the *Safety and Warranty Guide* or *HMM*, go to <http://www.lenovo.com/support/>.

This section provides instructions on how to replace a mouse.

1. Remove any media (diskettes, CDs, or tapes) from the drives, shut down your operating system, and turn off all attached devices.
2. Unplug all power cords from electrical outlets.
3. Locate the mouse connector.

Note: Your mouse may be a USB connector. Depending on where your mouse is connected, see "Locating the connectors on the rear of your computer" on page 2 or "Locating the connectors on the front of your computer" on page 1.




4. Disconnect the failing mouse cable from the computer.
5. Connect the new mouse to the appropriate connector on the computer.
6. Go to "Completing the parts replacement" on page 37.

Completing the parts replacement

After working with parts, you need to close the computer cover and reconnect any cables, including telephone lines and power cords. Also, depending on the part that was replaced, you might need to confirm the updated information in the Setup Utility program.

1. Ensure that all components have been reassembled correctly and that no tools or loose screws are left inside your computer.
2. Clear any cables that might impede the replacement of the cover.
3. Lower the drive bay assembly.
4. Make sure all cables are routed correctly through the cable clip **1**.



5. Close the computer cover.
6. Reconnect the external cables and power cords to the computer. See “Locating the connectors on the rear of your computer” on page 2.
7. If you are replacing the system board, you must update (flash) the BIOS. To update the BIOS, see “Updating (flashing) BIOS from a diskette or CD-ROM” on page 38.
8. To update the configuration, see “Using the Setup Utility” in the *User Guide* that was included with your computer.

Note: In most areas of the world, Lenovo requires the return of the defective CRU. Information about this will come with the CRU or will come a few days after the CRU arrives.

Updating (flashing) BIOS from a diskette or CD-ROM

Important

Start the Setup Utility program to view your system information. See “Using the Setup Utility” in your *User Guide* or the *Hardware Maintenance Manual*. If the serial number and the machine type/model listed on the Main menu do not match what is printed on the label of your computer, you must update (flash) the BIOS to change the serial number and the machine type/model.

To update (flash) the BIOS from a diskette or CD-ROM, do the following:

Note: An optical USB diskette drive is required to update (flash) BIOS from a diskette.

1. Insert a system program update (flash) diskette or CD-ROM into the diskette drive or optical drive. System program updates are available at <http://www.lenovo.com/support/> on the World Wide Web.

Note: To insert a CD-ROM into the optical drive, the computer must be turned on.

2. Turn on the computer. If it is on already, you must turn it off and back on again. The update begins.
3. When you are prompted to select a language, press the number on your keyboard that corresponds to the language and then press Enter.
4. When prompted to change the serial number, press Y.
5. Type in the seven character serial number of your computer and then press Enter.
6. When prompted to change the machine type/model, press Y.
7. Type in the seven character machine type/model of your computer and then press Enter.
8. Follow the instructions on the screen to complete the update.

Appendix. Notices

Lenovo may not offer the products, services, or features discussed in this document in all countries. Consult your local Lenovo representative for information on the products and services currently available in your area. Any reference to a Lenovo product, program, or service is not intended to state or imply that only that Lenovo product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any Lenovo intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any other product, program, or service.

Lenovo may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

*Lenovo (United States), Inc.
500 Park Offices Drive, Hwy. 54
Research Triangle Park, NC 27709
U.S.A.
Attention: Lenovo Director of Licensing*

LENOVO GROUP LTD. PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some jurisdictions do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. Lenovo may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

The products described in this document are not intended for use in implantation or other life support applications where malfunction may result in injury or death to persons. The information contained in this document does not affect or change Lenovo product specifications or warranties. Nothing in this document shall operate as an express or implied license or indemnity under the intellectual property rights of Lenovo or third parties. All information contained in this document was obtained in specific environments and is presented as an illustration. The result obtained in other operating environments may vary.

Lenovo may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Any references in this publication to non-Lenovo Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this Lenovo product, and use of those Web sites is at your own risk.

Any performance data contained herein was determined in a controlled environment. Therefore, the result obtained in other operating environments may

vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Television output notice

The following notice applies to models that have the factory-installed television-output feature.

This product incorporates copyright protection technology that is protected by method claims of certain U.S. patents and other intellectual property rights owned by Macrovision Corporation and other rights owners. Use of this copyright protection technology must be authorized by Macrovision Corporation, and is intended for home and other limited viewing uses only unless otherwise authorized by Macrovision Corporation. Reverse engineering or disassembly is prohibited.

Trademarks

The following terms are trademarks of Lenovo in the United States, other countries, or both:

Lenovo
ThinkCentre

IBM is a trademark of International Business Machines Corporation in the United States, other countries, or both.

Other company, product, or service names may be trademarks or service marks of others.

ThinkCentre®

Part Number: 41X6186

Printed in USA

(1P) P/N: 41X6186

